

5V Input 6A 1.25MHz 15µA Low Iq FAST-PWM Synchronous Step-Down Converter

DESCRIPTION

The MT3036 is a 6A high efficiency constant on-time controlled synchronous step-down converter. It operates with input voltage from 2.5V to 6V and provide output range from 0.6V to as high as input level, thanks to its 100% duty cycle operation. Its advanced constant on-time control Fast-PWM scheme simplifies loop compensation and offers excellent load transient response while maintaining a relatively constant 1.25MHz switching frequency. MT3036 consumes extremely low 15µA quiescent current hence achieves superior light load efficiency. The high gain error amplifier in the control loop provides excellent load and line regulation. For fault tolerant operation, MT3036 has cycle-by-cycle current limit protection and hiccup mode for short circuit or over-load condition.

MT3036 is available in 10 leads DFN 3mmx3mm package and ideal for high performance, portable applications.

FEATURES

- Wide Input Range from 2.5V to 6V
- High Efficiency up to 97%
- Output Voltage as low as 0.6V
- 100% Duty Cycle Operation
- +/-1.5% 0.6V Feedback Voltage Accuracy
- 1.25MHz Pseudo Constant Switching Frequency
- 15µA Quiescent Current
- Continuous Output Current up to 6A
- Built-in 30mΩ HS and 25mΩ LS Power Switches
- Cycle-by-cycle Current Limit Protection
- Hiccup Mode for Short Circuit and Over-Load Protection
- Open Drain Power Good Indication with Internal Pull-up Resistor
- Thermal Shutdown Protection
- Stable with low ESR ceramic Output Capacitors
- Available in a Small DFN3x3_10L Package
- Pb-Free RoHS Compliant

APPLICATIONS

- Solid-State and Hard Disk Drives
- Portable / Handheld Devices
- WiFi Module, Set-top Boxes
- DC/DC Micro Modules

TYPICAL APPLICATIONS

